

Full Load Current Table for the Circuit Breakers

Three Phase – 60 Hz

Power		Voltage		
kW	KVA	600 V	480 V	208 V
		FLC	FLC	FLC
250.0	312.5	300.7	375.9	867.4
300.0	375.0	360.9	451.1	1040.9
350.0	437.5	421.0	526.2	NA
400.0	500.0	481.1	601.4	NA
450.0	562.5	541.3	676.6	NA
500.0	625.0	601.4	751.8	NA
550.0	687.5	661.6	827.0	NA
600.0	750.0	721.7	902.1	NA